

Overview

The following list depicts compatibility between Lutron dimmers and other manufacturer's Electronic Low Voltage (ELV) transformers. The compatibility criterion is limited to dimming performance, reliability, and excessive audible and electrical noise. Please be aware that the ELV transformer design and/or components may have changed since the execution of the compatibility testing, therefore, this document is not a guarantee of compatibility.

PLEASE NOTE using Lutron's reverse phase (trailing edge) dimmers (ie: GXI) with an ELV transformer will give the following benefits:

- Reduced acoustic noise
- Reduced RFI (radio frequency interference)
- Increased lifetime of the dimmer and transformer

This is in comparison with using a standard incandescent forward phase (leading edge) dimmer with an ELV transformer. Reduced acoustic noise will mean quieter lamps, transformers and dimmers. Reduced RFI is especially important for the performance of sensitive Audio or Video systems, which are installed in close proximity. Keep mains voltage cables at least 50cm from sensitive signal wires. When crossing, keep cables at right angles to sensitive signal wires.

For further information, please refer to Lutron's Application Note #19 at <http://www.lutron.com/applicationnotes/362219b.pdf>

Recommended Transformers From Lutron®

ELVXF-60-XXX series 230 / 240V 60W
ELVXF-105-XXX series 230 / 240V 105W

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturer's instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Make	Model	Date Tested	Description	Forward phase (Leading Edge)					Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	Reverse phase neutral connection dimmers*	
ACDC Lighting	Nemesis Mains	Mar. 3, 2008	240V 120W				✓				✓	
Altima	13.0060.04	Mar. 24, 2008	240V 20-60W								✓	
	13.0076.04	Mar. 20, 2008	240V 20-75W								✓	
	13.1105.04	Mar. 24, 2008	240V 35-105W				✓				✓	
	13.3003	Mar. 25, 2008	240V 300W									
	SA.4026	Mar. 24, 2008	240V 70-210W				✓				✓	
Aurora	A2-105	Dec. 29, 2009	240V 35-105W				✓				✓	
	A2-H60	Dec. 29, 2009	240V 20-60W	✓			✓				✓	
	A2-L60	Dec. 29, 2009	240V 20-60W	✓	✓	✓	✓	✓			✓	
	AU-60S	Jun 18, 2003	240V 20-60W								✓	
	AU-60TA	Dec. 29, 2009	240V 20-60W		✓	✓	✓	✓			✓	Audible noise w/ forward phase
	AU 60T3	Jan. 19, 2007	240V 20-60W		✓		✓	✓			✓	
	AU-E60	Dec. 29, 2009	240V 10-60W				✓				✓	
	AU-E105	Dec. 29, 2009	240V 20-105W		✓		✓	✓			✓	
	AU-PD60	Dec. 29, 2009	240V 20-60W	✓	✓		✓				✓	
	AU-S60	Dec. 29, 2009	240V 20-60W				✓				✓	
	AU-SF60A	Oct. 15, 2004	230-240V 20-60W								✓	
	AU-SF60T	Dec. 29, 2009	240V 20-60W								✓	
	AU-SM60TL	Dec. 29, 2009	240V 20-60W							✓	✓	Not for use with NGRX-PB-AU.
	AU-SM105	Dec. 29, 2009	240V 20-105W								✓	
	LUT-60	Jan. 19, 2007	240V 20-60W		✓	✓	✓	✓			✓	
Stealth 60	Jan. 19, 2007	240V 20-60W		✓		✓	✓			✓		
Click Lighting	TR160	Oct. 22, 2008	240V 20-60VA								✓	
	TR260	Oct. 23, 2008	240V 20-60VA								✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)					Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	Reverse phase neutral connection dimmers*	
Dais	DA-E60	Dec. 29, 2009	240V 20-60W	✓	✓	✓	✓	✓			✓	Louder audibly with QSG-CE
	DA-J60	Dec. 29, 2009	240V 20-60W								✓	
Deluce	DLT60AR	June 6, 2006	220-240V 20-60VA								✓	
Doyle & Tratt	Varilight YT50	May 15, 2009	230V 0-50W						✓		✓	
	Varilight YT70	Oct. 15, 2004	230-240V 20-60W								✓	
	Varilight YT105	May 15, 2009	230V 0-105W						✓		✓	
	Varilight YT250	May 15, 2009	230V 0-250W						✓		✓	
Electric City	EC-60	Mar. 3, 2010	240V 20-60W								✓	
Elite	EL-60		230-240V 20-60W								✓	
ELLE.PI	AU-KIOS	Dec. 12, 2007	230-240V 35-105W								✓	
	1.AU-K60	Dec 13, 2007	230-240V 20-60W								✓	
Emcolite	EMC E20-60	Dec 13, 2002	240V 20-60W							✓	✓	
Enigma	EHT4-101	Sep. 4 2007	240V 50W				✓				✓	
Enlite	EN-E60	July 14, 2004	240V 20-60W								✓	
	EN-SC60	Dec. 29, 2009	240V 60W		✓	✓	✓	✓			✓	
Erco	Pollux	Mar. 9, 2006	230V 50W								✓	Built in dimmer must be set full on
EREA	Code 4597	Nov 9, 2009	230-240V 20-7W								✓	
	Code 4595	Sep. 5, 2006			✓							Audibly noisy
	Code 6660	Nov 9, 2009	240V 20-70W				✓				✓	24V output
Ereatronic	60i/K	Feb. 27, 2003	220-240V 20-60W								✓	
	60i/T	Dec 22, 2008	220-240V 20-60W								✓	
Eterna Lighting	DET-65 VA									✓		
	Model ET60D	Feb. 24, 2006	240V 20-60VA								✓	
ETI	W.X 60	July 14, 2004	230V 20-60W								✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)					Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	Reverse phase neutral connection dimmers*	
ETI	W.X105	Jan. 27, 2005	230V 20-105W								✓	
	PTE200	Jan. 25, 2005	230V 100-200W								✓	
EuroLite	WT-60L-75	Mar. 21, 2001	240V 75W		✓			✓			✓	
Europhase	LET-75	Jan. 21, 2006	120V 75W		✓		✓	✓			✓	
Gitronica	GET 105 FI/ V1U	June 3, 2002	230V 35-105W								✓	
GroupB	LT60W	Nov 13, 2008	240V 60W		✓	✓	✓	✓			✓	
GVP SLR	ET-24	Mar. 13, 2008	230V 100W								✓	
	HD-24	Mar. 11, 2008	230V 200W								✓	
Hatch	HA12-75R	Sep 27, 2005	120V 75W								✓	
	IS12-75	Mar. 19, 2001	120V 75W								✓	
	RS12-60M	Sep 20, 2005	120V 60W				✓				✓	
	RS12-80M	Sep 14, 2005	120V 80W				✓	✓			✓	
	RS12-108	Sep 21, 2005	120V 100W								✓	
	RS12-150	Sep 27, 2005	120V 150W								✓	
	VS12-60	Nov 20, 2001	120V 60W				✓				✓	
Halolite	HA-60	Dec. 29, 2009	240V 20-60W	✓	✓		✓				✓	
	HA-105	Jan. 19, 2007	240V 35-105W		✓	✓	✓	✓			✓	
	HA-150	Dec 10, 2004	240V 50-150W								✓	
	HA-E60	Jan. 19, 2007	240V 20-60W		✓	✓	✓	✓			✓	
	HA-SF60A	Dec. 29, 2009	240V 20-60W				✓				✓	
Hamilton	HAM-60	June 8, 2010	240V 20-60W		✓		✓				✓	
Hua Yi Lighting	ET-50E	Dec 15, 2009	220-240V 20-50W								✓	
Huco	EN 61046	Oct. 15, 2004	230-240V 20-60W								✓	
	EN 61047	Oct.15, 2004	230-240V 20-60W								✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)				Reverse Phase (Trailing Edge)			Miscellaneous notes	
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-		Reverse phase neutral connection dimmers*
Infuse	Model 113	Oct. 15, 2004	240V 10-60W							✓		
Insta	SNTI 105	July 14, 2004	230-240V 20-105W							✓		
IBL	4103	Not available	Not available							✓		
	4104	Jan. 19, 2007	230-240V 20-60W						✓	✓		
	4105	Jan. 19, 2007	230-240V 20-75W		✓				✓	✓		
	4106	Jan. 19, 2007	230-240V 35-105W		✓			✓		✓		
	4106.00	Jun 24, 2009	230-240V 35-105W							✓		
	4232.00	Apr. 27, 2009	240V 200W							✓		
	4350	Jan. 19, 2007	230-240V 20-60W							✓		
	4351	Jan. 19, 2007	230-240V 35-105W		✓			✓		✓		
	4360	Jan. 19, 2007	240V 50-150W					✓	✓		✓	
	4370.00	Jun 25, 2009	230-240V 70-210W								✓	
	4611.00	Not available	Not available							✓		
	4616.00	Not available	Not available							✓		
	4630.00	Apr. 7, 2006	230-240V 20-60W		✓	✓	✓	✓			✓	Telume not tested.
	4630	Jan 19, 2007	230-240V 20-60W								✓	
	4632	Jan. 19, 2007	230-240V 20-60W						✓		✓	
	4632.00A	Jun 24, 2009	230-240V 40-60W				✓				✓	
	4633	Feb. 26, 2008	240V 60W								✓	
4640.00	Jul. 7, 2006	230-240V 35-105W				✓						
ELT 60DLA	Jun 24, 2009	230-240V 20-60W				✓				✓		
Impact	BLE060	Sep. 9, 2002	230-240V 20-60W							✓		
ITEC	ET050/D	Not available	Not available							✓		
	ET60B	Not available	Not available							✓		

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)				Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	
JCC Lighting	JC4014	Mar. 6, 2003	240V 20-60W							✓	
	JC4018	Mar. 23, 2010	240V 20-60W							✓	
	JC4019	Jul. 21, 2005	240V 20-60VA				✓			✓	
	JC4020	Mar. 23, 2010	240V 20-60W							✓	
	JC4030	Mar. 23, 2010	240V 20-60W							✓	
John Cullen Lighting	TE05012DT	Jan. 25, 2005	240V 20-50VA							✓	
LCI	ET 105M	May 11,2009	240V 20-105W							✓	
	ET 105P	Apr. 25,2009	234-240V 20-105W				✓			✓	Audibly noisy with GP
LighTech	LET 60	Mar. 11,2010	120V 20-60W			✓	✓		✓	✓	
	LET 60	Jan. 19,2007	230V 60W		✓	✓	✓	✓		✓	Each transformer = 240W lamp
	LET 75	Jun. 6, 2007	120V 75W				✓			✓	Compatible with Stanza ND
	LET 75	Jun. 22, 2006	230V 75W				✓			✓	Compatible with Stanza ND
	LET 75	Jan. 19,2007	240V 75W					✓		✓	
	LET 75BF	Apr. 25,2007	120V 75W		✓		✓	✓		✓	
	LET 75-R	Jun. 6, 2007	120V 75W				✓			✓	Compatible with Stanza ND
	LET-151	Nov 11, 2005	120V 50-150W		✓		✓	✓		✓	
	LET 210/240	May 11,2009	240V 70-210W 24V				✓			✓	Audibly noisy with GP
LET303 DC240-24	Mar. 14, 2006	240V 300W		✓	✓	✓	✓		✓		
Lighting Services	BP75	Feb. 7, 2001	120V 70W load				✓				
Litenet	E21260	Sep 28, 2005	220V 35-60W							✓	
Litetronics	ET50CE	Oct. 30, 2002	230-240V 20-70W							✓	
Luminaires	541382313000	Mar. 28, 2005	240V 60VA							✓	
Lytlec	LEB60D	Not available	Not available							✓	
MAE	MA-60	Dec. 29, 2009	240V 10-60W				✓			✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)				Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	
Magnatek	HPD/60 NV	Jan. 22, 2001	230V 20-60W			✓	✓	✓		✓	
Massgrove	MT-60	Not available	Not available						✓		
Mode	ET-55 C-240-RD	Aug. 8, 2005	240V 20-55VA				✓			✓	
	ET-060-C-240-RD	Aug. 8, 2005	230-240V 20-60VA				✓			✓	
	ET-105-C-240-RD	Jan. 19, 2007	240V 20-105VA		✓		✓	✓	✓	✓	Not for use with NGRX-PB-AU.
	ET-105-P-240-RD	Mar. 14, 2005	240V 35-105W			✓	✓	✓		✓	Do not use with NGRX-PB-AU.
	ET-215-T-240-RD	Mar. 28, 2005	240V 50-215VA			✓	✓			✓	
	ET-315-T-240-RD	Mar. 29, 2005	240V 50-315VA				✓		✓	✓	
	ET-E50220-230	Aug. 8, 2005	Not available								
	MOE-105-C-240	Jan. 19, 2007	240V 105VA		✓		✓	✓	✓	✓	
PUMA	Jan. 19, 2007	240V 105VA				✓	✓	✓	✓		
Osaka Koha	Unknown	Mar. 15, 2006	100V 100W		✓	✓	✓	✓		✓	Telume not tested.
Odelic	0J068016	Jul. 19, 2001	100V 75W				✓				
Osram	ECO-ET 60/220/230	Dec. 28, 2007	220V 20-60W				✓			✓	
	ECO-ET 105/220	Jan. 3, 2006	220V 35-105W				✓			✓	
	Parrot 70/220-240 I	Mar. 19, 2009	220-240V 70W							✓	
	Parrot 105/220-240 I	Mar. 19, 2009	220-240V 105W							✓	
	ET-Redback	Jun 23, 2009	230-240V 60W				✓			✓	
	HTM 70-230/240	Jul. 1, 2002	230-240V 20-70W						✓	✓	
	HTM 105-230/240	Jul. 1, 2002	230-240V 35-105W						✓	✓	
Oxford	ET60T-2	Jan. 23 2006	240V 20-60VA							✓	
Phillips	ET-E 60	Dec. 13, 2007	220-240V 20-60W		✓	✓	✓	✓		✓	
	ET-S 50	Dec. 18, 2003	220-240V 50W				✓			✓	
	ET-S 105	Dec. 18, 2003	220-240V 105W							✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)				Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	
Phillips	ET-S 150	Dec. 20, 2003	220-240V 150W				✓			✓	
PLC	PLC-TF2050	Dec 15 th 2009	220-240V 60W							✓	
Power Select Inc.	PS20B75S	Jan. 20, 2006	120V 75VA		✓		✓	✓		✓	
Power:Tran	ET60-3	Mar. 12, 2009	240V 60VA							✓	
RCG	HA127	Sep. 29, 2009	127V 50W (Brazil)		✓					✓	High RF noise production
Reggiani	1.09311.BV21	Not available									
Reiz	ET-60CN	Aug. 14, 2008	240V 20-80W							✓	
Relco Fox	60PFS	Jun. 11, 2003	240V 10-60W							✓	
Saxby lighting	Pico wolf 60	July 14, 2004	230-240V 10-60W							✓	
	ET 60T-R	Oct. 21, 2008	240V 60W							✓	
Seet 7	CK60-230M	Oct. 31, 2002	230-240V 20-60W							✓	
Seet	HR-60	Dec. 17, 2002	230V 20-60W							✓	
	HA 60C	Jan. 19, 2007	230V 20-60W		✓	✓		✓		✓	
	Plus	Apr. 27, 2009	230V 20-60W							✓	
	Plus code 7730	Jan. 19, 2007	230V 20-60W		✓	✓	✓	✓		✓	
	Prime	Jan. 19, 2007	230V 20-60W		✓	✓	✓	✓		✓	
Self	ET-60T-2	Apr. 7, 2006	220-240V 10-60VA							✓	Telume not tested.
SKOT	ET60- (mini mole)	April 21, 2004	230V 20-60W							✓	
Sky	PTM/60 KD	Oct. 28, 2002	240V 20-60W							✓	
SLI Sylvania	Lumitroic 60	Nov. 11, 2009	240V 20-60W		✓	✓	✓	✓		✓	
Slimmer Teamluxe	2005-DEL60	Not available								✓	
	2006-DE60	Dec. 13, 2002	240V 20-60W							✓	
Smac-Lite	FA-LVT60	Aug. 29, 2005	240V 20-60VA				✓	✓		✓	
Speedy	TE-0070 C101	Jun. 22,2005	230-240V 20-70W				✓			✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)					Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	Reverse phase neutral connection dimmers*	
Targetti	Puma 60	May 9, 2003	230-240V 20-60W								✓	
TCI	X 70	Mar. 9, 2001	230V 20-70W								✓	
	MW.X 60	Mar. 9, 2001	230V 20-60W								✓	
	LS 50	Mar. 9, 2001	230V 20-50W								✓	
	Pico Wolf X60	Dec. 12, 2008	240V 60W								✓	
	Pico Wolf 105	Dec. 12, 2008	240V 105W								✓	
Technolite	ELT.60	May 11, 2006	230-240V 50W				✓				✓	Telume not tested.
	Mini.M50	May 10, 2006	220-240V 50W				✓				✓	Telume not tested.
Teclite	ET60T-5	Oct. 15, 2004	230-240V 20-60W								✓	
Trajectoire	Eclairage 8241	Apr. 1, 2003	230-240V 20-60W								✓	
Tridonic	TE-0060	Dec. 5, 2007	230-240 20-60W								✓	
	TE-0070 C101	Jun. 6, 2005	230-240V 20-70W				✓				✓	
	TE-EM105	Jun. 3, 2002	230V 35-105W								✓	
	TE-SA 0210	May 18, 2001	230-245V 210VA								✓	
Tridonic. Atco	Viper 60VA ET	Mar. 19, 2009	230-240V 60VA								✓	
	Viper 105VA	Mar. 19, 2009	230-240V 105VA								✓	
	Possum Elec. Tranny	Jun 24, 2009	230-240V 60W								✓	
	Speedy TE-0105 C101	Jun 24, 2009	230-240V 35-105W								✓	
Tronic Trafo	Insta SNTI 105	May 5, 2009	240V 105W								✓	
	SNT 105/SR	Dec. 4, 2001	230V 100W								✓	
Universal Lighting	UPE60	Apr. 6, 2001	240V 100W								✓	
Universal Lighting	UP-200	Feb. 7, 2001	240V 50-200VA								✓	
Vossloh Schwabe	EST60/12.634	Sep. 1,2009	240V 60W								✓	
	LitelineEST 105/12.381	Sep. 1,2009	240V 105W		✓	✓	✓	✓			✓	

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.
The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.

Continued from previous page...

Make	Model	Date Tested	Description	Forward phase (Leading Edge)					Reverse Phase (Trailing Edge)			Miscellaneous notes
				QSG-CE	GRX-3000- QSG-	NGRX-PB-	GP Card	LP Module	RISU-452B- RNSU-452B-	TM-ELV500- TIR-ELV500-	Reverse phase neutral connection dimmers*	
W.A.C	EN-1260-R2	Dec. 6, 2005	120V 60W		✓		✓	✓			✓	
	EN-12150-R-AR	Mar. 17, 2005	120V 35-150W				✓				✓	
	EN-1250-TH-AR	Mar. 22, 2005	120V 50W								✓	
	EN-1275-RB-AR	Dec. 5, 2005	120V 75W		✓		✓	✓			✓	
	EN-12PY-AR	Dec. 12 2005	120V 100-250W								✓	
Wang House	WH-602E6F	Dec. 18, 2002	230V 60W								✓	
Yamagiwa	Z6129	Jun. 12, 2001	100V 60W				✓				✓	
	NKB751123	Nov. 8, 2001	100V 75W		✓		✓	✓			✓	
	Z6112	Sep. 25, 2001	100V 17W				✓				✓	
	Z6130	Sep. 25, 2001	100V 17W				✓				✓	
	Z6132	Sep. 25, 2001	100V 36W				✓				✓	
	T5170S	Oct. 31, 2001	100V 50W		✓		✓	✓			✓	
	NKB501121	Nov. 7, 2001	100V 50W		✓		✓	✓			✓	
Zenith	IEC 61046	Dec. 12, 2007	240V 10-60W								✓	

* Reverse phase neutral connection dimmers are:

4A/4E module

ELVI-

GXI-3104-

PHPM-PA-DV-WH

This document is designed to serve as a guide on the compatibility of Lutron systems with European electronic control gear and electronic transformers.

Results may be different under actual field conditions. The tests were carried out on the product versions available at the time of testing (see dates listed in the chart). Other manufacturers may change their products which may impact their compatibility with Lutron dimmers.

The combination of Lutron dimmers and Electronic Transformers or Electronic Control gear should be installed in accordance with each manufacturers instructions and in accordance with National and Local Electrical codes and regulations and in accordance with any application notes for that combination indicated in the chart.

The products were tested to confirm system compatibility. LUTRON WILL NOT BE RESPONSIBLE FOR IMPROPER USE OF ANY PRODUCTS.

Lutron cannot guarantee the quality of any non-Lutron products in this list.